## White Spaces

Need for more spectrum to satisfy the growing demand.

Spectrum refarming: opportunistic spectrum usage

Many standard efforts

Only one formally approved by FCC in US and Ofcom in UK

Several trials have been conducted

**Evolution of Spectrum usage** 

#### Fixed allocation


- 1) Government assigned
- 2) Auction
- 3) Beauty Contest

#### Dynamic Spectrum allocation

http://www.apc.org/en/faq/citizens-guide-airwaves



# **Television White Spaces**





Friday, June 14, 2013


# **Television White Spaces: definition**


- a) The spectrum that has been assigned to TV broadcasting but it is not currently being used. This applies particularly to developing countries, in which there has been no economic incentive for broadcaster to use every available TV channel.
- b) The spectrum that must be left free in between two analogous TV channels to prevent interference.
- c) The spectrum that has been reclaimed as a consequence of the transition to digital terrestrial TV, which is more spectrum efficient.

See: "On the relevance of using affordable tools for white spaces identification" at <a href="http://wireless.ictp.it/">http://wireless.ictp.it/</a>
<a href="publications.html">publications.html</a>









#### **TV Band Devices Standards**

IEEE 802.22 for long range transmission Wireless Regional Area Networks (WRAN)

IEEE 802.11af for short range, OFDM PHYs with 5, 10 and 20 MHz channel widths

IEEE 802.15.4m for device control and command applications IEEE 802.19 for coexistence among multiple TV white space networks

IEEE DySPAN aimed at Dynamic Spectrum Access Networks IEEE 802.16h originally meant for the 3650-3700 MHz contention band but now also specified for the TV bands ECMA 392 directed at personal and portable wireless devices, Weightless mainly focused at Machine-to-Machine interactions IETF PAWS covering the specification of the mechanism for discovering a white spaces database and method for its access.

# Propagation advantages of TV bands

The superior propagation features of the lower frequencies bands for two way transmission have been proved in several trials of the CDMA 450 MHz technology, like the one in the Argentinian Patagonia operated by Cooperativa Telefonica de Calafate, with subscribers up to 50 km


from the base station.

This is due to three factors:

- a) Lower free space loss
- b) Better diffraction efficiency
- c) Lower building attenuation



#### **Wireless Standards**




# Software Defined Radio (SDR)



- Conventional Approach

  Each radio interface is implemented through Integrated Circuits conceived for a set of specific functions
- Wireless device characteristics are fixed



#### Software Radio approach:

- the wireless terminal is reconfigurable via software
- It can be easily updated to ne or later versions of the air interface and allows multiple interfaces to be supported

# ITU approved SDR definition

Software-defined radio is a radio transmitter and/ or receiver employing a technology that allows the RF operating parameters including, but not limited to, frequency range, modulation type, or output power to be set or altered by software, excluding changes to operating parameters which occur during the normal pre-installed and predetermined operation of a radio according to a system specification or standard."

Source: Report ITU-R SM.2152.

# ITU approved Cognitive Radio definition

"Cognitive radio system is a radio system employing technology that allows the system to obtain knowledge of its operational and geographical environment, established policies and its internal state; to dynamically and autonomously adjust its operational parameters and protocols according to its obtained knowledge in order to achieve predefined objectives; and to learn from the results obtained."

Source: Report ITU-R SM.2152.

# **Capabilities of Cognitive Radio**

Spectrum Sensing

Spectrum Sharing (by agreement or compulsory)

Location Identification by the Mobile

Network/System/Service Discovery

Frequency Agility

**Dynamic Frequency Selection** 

Avoid co-channel operation

Adaptive Modulation/Coding


**Transmit Power control** 

Dynamic System/Network Access

Mobility and Connection Management

**Security Management** 

# **Sensing and Communicating**



# Sensing

Sensing clock is separated from transceiver

Multiple sensing strategy: Coarse and Fine

Sensing during communication and also at idle times

Critical computation is performed in the analog domain

## **Sensing Techniques**


Multi Resolution Spectrum Sensing Sensing (MRSS)

Coarse Sensing: Detect the presence of signal, for instance by Fourier transform

Analog Autocorrelation (AAC)

Fine sensing: categorization of the signal type

# **Analog Auto Correlation**



# **Fine Sensing**

Detect the periodic features of the input signals unique to each modulation scheme or format

**AAC** can recognize the following signals: IS-95, WCDMA, EDGE,GSM, WiFi, WiMAX, ZigBee, Bluetooth, Digital Terrestrial Television (ATSC,DVB) etc.

#### Main features of IEEE 802.22

Spectrum Reuse, White Spaces, combatting the spectrum crunch.

Lower frequencies, greater range thanks to less attenuation by walls, greater diffraction and lower free space loss.


Lower energy consumption as compared with WiFi or ZigBee.

Non Line Of Sight propagation.

High spectrum efficiency.


Use of software defined radio (SDR) as a stepping stone towards Cognitive Radio (CR)

# Greater range because of lower frequency




### 802.22 Coverage

- BS can reach a CPE up to 100 km away at 22 Mb/s.
- From the CPE the range is 33 km if the EIRP is 4W
- TV frequency bands from 54 to 862 MHz
- Ideally suited for rural areas
- Modulation: 64 QAM, 16 QAM, QPSK, distance dependent



# Area of Coverage Comparison 40 km radius



Coverage with 5 GHz

Coverage with 470 MHz

http://www.carlsonwireless.com/products/ruralconnect-ip.html

#### 802.22

Protection of TV broadcasting

Protection of Part 74 wireless microphones

802.22.1 wireless microphone beacon

Quiet periods for sensing

Self-coexistence among WRAN systems

#### **Frame Structure**

**March 2009** 


doc.: sg-whitespace 09-0058r2

802.22 Frame Structure

Superframe = 160 ms

Frame = 10 ms

Superframe = 16 frames




Submission

Slide 6

Gerald Chouinard, CRC

## Frame



MAC Frame structure

# Regulatory Issues

#### Target performance

Items	Requirements			
Service Coverage	Typical 33 km ~ Max 100 km			
Active subscribers	Minimum 12 users			
Minimum Peak Throughput at Cell Edge	Forward link : 1.5 Mbps / subscriber (18 Mbps in total) Reverse link : 384 kbps / subscriber			
Spectral Efficiency	Minimum : 0.5 bps/Hz Typical : 3 bps/Hz → 18 Mbps for 6 MHz BW			
Service Availability	50% of locations & 99.9% of time			

### **Data Base Query**

In the U.S. radios authorized and operating as white space devices (TVBDs) are required to provide their geographic location, by means of a secure Internet connection, to a TV band database system authorized by the Commission. The database will return a list of authorized channels available for operation by the TVBD for its reported location.

#### **Base Station**



To use the system, a device first supplies its location to the database, using a frequency that is known to be permanently free in that area. The system then tells the device which other chunks of spectrum are available to use at that time

## 802.22 parameters

Data Rate

Spectrum Efficiency

Modulation

EIRP

Media ACCES

4.54 to 22.69 Mb/s

0.76 to 3.78 ((bit/s)/Hz)

QPSK, 16-QAM, 64-QAM

Local reg. dependent, typ. 4 W

OFDMA

Cyclic Prefix 1/4, 1/8, 1/16, 1/32

Duplexing Technique TDD (Time Division Duplex)

Number of CPE supported by BS 512

With 12 simultaneous users the minimum data rate per CPE would be 1.5 Mb/s downlink and 384 kb/s uplink


6, 7, 8 MHz

Channel Bandwidth


# Physical Layer (PHY)

- OFDMA
- WRAN typical propagation time from 25 μs to 50 μs
- 40 µs cyclic prefix preamble
- Flexible modulation and coding schemes (QPSK, 16QAM and 64QAM)
- 48 subchannels

#### Spectrum Management



#### **Database Service**



Structure of the IEEE 802.22 WRAN access to the database service

#### **Antennas**

- Each CPE would need two antennas: one omni and one directional
- Omni used for spectrum sensing and measurement
- Directional used for actual data communication.
- There might be need for a third antenna to perform database consultation, say through a cellular system

#### 802.22 in the UK

- The Communications Regulator, Ofcom UK, has announced the introduction of licence exempt White Space wireless broadband technology in the UK. This uses the radio spectrum that exists between digital terrestrial TV channels to deliver internet access over a Wireless Regional Area Network (WRAN).
- Ofcom has decided to allow multiple third-party providers to develop databases, which it believes will create a competitive marketplace and incentivise operators to provide the best database service to consumers.

#### 802.22 in South Africa

- TV white spaces can open up low-cost high-speed internet across Africa: All we need is the regulatory goahead.
- "Unused TV white spaces could be the way to get highspeed wireless internet to millions in Africa including those who have been enforcedly "offline" till now because they live outside major cities.

### Example of commercial device specs

Frequency Bands UHF 470-786 MHz (US and ETSI)

Channel Spacing 6 MHz (US), 8 MHz (ETSI)

Bandwidth 100 kHz (M2M) to 4.5 MHz (Rural BB)

Modulation QPSK, 16QAM

Data Rates 4, 6, 8, 12, and 16 Mb/s

Data Rate Control Dynamic or fixed

Receive Interface Proprietary to reduce co-channel interference

RX Sensitivity (6 or 8 MHz) -89 dBm for 10-6 BER using QPSK 1/2

-86 dBm for 10-6 BER using 16QAM 1/2

RX Blocking Resistance -50dBm TV transmission on chan N+2

-20 dBm cellular station transmissions

RX Max Signal -16dBm with full linearity

Operating Mode TDD (Time Division Duplexing) or

optionally FDD for point-to-point use

User Ports Mini-B USB or 10/100 baseT Ethernet

## **Example of commercial device specs**

#### **NETWORK SPECIFICATIONS**

Multipoint Client Capacity 4096

Typical Client Loading 60 clients with 3Mb/1Mb residential SLA

Management Web-based browser using https interface

End-to-End Latency 30-100 ms typ.

REGULATORY SPECIFICATIONS

ACP and Spectrum Mask Meets FCC and Ofcom specifications

-55 dBr +/- 3 MHz relative to 12.2 dBm

#### **ENVIRONMENTAL SPECIFICATIONS**

Operating Temperature -40° to 55° C
Operating Humidity Up to 95%, non-condensing

Shock and Vibration MIL-STD-810

Security Mechanism WPA2/AES-128 bit shared secret key

### Example of commercial device specs

#### **BASE STATION**

RF Transmit Power Antenna System Antenna Connector Unit Dimensions Weight Mounting

#### **CPE**

**RF Transmit Power** Antenna System **Antenna Connector Unit Dimensions Enclosure Material** Weight Mounting Voltage **Power Consumption** 

+30dBm level across band within +/- 1dB 4.8 dBi Omni, MIMO Space Diversity option "F" type female 75 Ohms, 1.3:1 VSWR 19.6" x 6" x 1.75" 5 lbs 19 inch EIA 1 unit rack

+27dBm level across band within +/- 1dB 12 dBi, 15° Beamwidth, 1.5:1 VSWR "F" type female 75 Ohms 9.20" x 7" x 1.6" Anodized aluminum 3 lbs 12 oz Outdoor on Mast 100-240 VAC, 50-60 Hz or 12 VDC Tx: 12W, Rx: 5W, Idle: 3W

#### **Another Manufacturer**

#### Specifications:

Electrical

RF Module frequency bands (factory selectable)

VHF 174 - 216 MHz (TV Channels 7-13)

UHF 470 - 698 MHz (TV Channels 14-52)

RF Transmit Power 10 to 20 dBm with ATPC

Noise Figure 4 dB

Spurious & Harmonic Emissions FCC Part 15 compliant

Data Rates 2.0 or 3.1 MB/s Modulation FSK, SOQPSK

Channel Bandwidth 6 MHz

Frequency Selection 100 kHz steps

Selectivity >60 dB

Operating mode Half-duplex or simplex

User Port Ethernet (10/100 BT)

Mechanical

Dimensions 3.25" x 5.5" x 1.6"

Enclosure material AL Anodized

Weight (w/o mount) 1.2 lb

Mounting

Hub Optional bracket for DIN rail or wall

Remote/Subscriber 1" - 2" pole

Connectors


Antenna Type N (F)

Ethernet/Power (18 or 24 VDC) Watertight RJ45

# Antenna Example, other m.

Specifications	Units	Value	
Electrical			
Frequency Range	MHz	470-930	
Nominal Gain	dBi	10	
Number of Elements		48	
Polarization		H or V	
Horizontal Beamwidth	Deg	65	
Vertical Beamwidth	Deg	65 20	
Front to Back Ratio	dB		
Power Rating	W	50	
Impedance	Ohms	50	
Return Loss (min)	dB	10	
Lightning Protection		DC Gnd	
Connector		Type N(F)	
Mechanical			
Length	in/cm	38/96	
Width	in/cm	13/32	
Weight	lbs/kg	2.4/5.3	
Rated Wind Velocity (No ice)	mph	100/161	
Rated Wind Velocity (0.5" ice)	m/hr-km/hr	85/137	
Pole Mast OD Supported	in/cm	1-2/2.5-5	

#### Antenna Example, other m.



## Weightless Standard

Weightless is a royalty-free open standard focussed on M2M (Machine to Machine Communication) in white spaces. The draft Weightless specification is available at <a href="http://www.weightless.org/what-is-weightless">http://www.weightless.org/what-is-weightless</a> and is aimed at: great flexibility in the data rate provided depending on the application, range and environment. It uses frequency hopping at the frame rate to minimize the impact of interference - both received and caused and a design that minimizes costs and power consumption employing a highly efficient MAC-level protocols that result in small headers per transmission and hence little overhead even when the payload is only a few bytes long.

# Weightless Standard Meant for M2M applications

Table 7.1 Overview of variation in PHY parameters [Source: Weightless standard]

Modulation scheme	Coding rate	Spreading factor	Downlink PHY data rate (Mbps)	Required SNR before FEC & spreading (dB)	FEC gain (dB)	Spreading gain (dB)	Required SNR for 10 <sup>-4</sup> BER (dB)	Noise figure incl. digital losses (dB)	Required signal level at Rx input (dBm)
16-QAM	1	1	16.0	18.5	0.0	0	+18.5	6.0	-82.5
16-QAM	3/4	1	12.0	18.5	4.0	0	+14.5	6.0	-86.5
16-QAM	1/2	1	8.0	18.5	7.5	0	+11.0	6.0	-90.0
QPSK	3/4	1	6.0	11.5	4.0	0	+7.5	6.0	-93.5
QPSK	1/2	1	4.0	11.5	7.5	0	+4.0	6.0	-97.0
BPSK	1/2	1	2.0	8.5	7.5	0	+1.0	6.0	-100.0
BPSK	1/2	4	0.5	8.5	7.5	6.0	-5.0	6.0	-106.0
BPSK	1/2	16	0.125	8.5	7.5	12.0	-11.0	6.0	-112.0
BPSK	1/2	63	0.040	8.5	7.5	18.0	-17.0	6.0	-118.0
BPSK	1/2	255	0.010	8.5	7.5	24.0	-23.0	6.0	-124.0
DBPSK	1/2	1023	0.0025	10.5	7.5	30.0	-27.0	6.0	-128.0

#### **Thank You**

ICTP (International Centre for Theoretical Physics)

T/ICT4D Lab

Marco Zennaro

Carlo Fonda

Ermanno Pietrosemoli

http://wireless.ictp.it